



### About Product

In gasoline and diesel portable generators, the GO-BUSINESS GO-MOTOR generator set offers high performance and reliability. For all manufactured generator sets, prior product testing and factory manufacturing testing are carried out.

### POWER

| VOLTAGE | Standby Power (ESP) |      | Prime Power (PRP) |      | Amper | PWR (HP) |
|---------|---------------------|------|-------------------|------|-------|----------|
|         | kVA                 | kW   | kVA               | kW   | A     | hp       |
| 220     | 3,88                | 3,10 | 3,50              | 2,80 | 12,5  | 7,00     |

### General Features

|                       |                       |
|-----------------------|-----------------------|
| Model Name            | GO-BJE4000            |
| Fuel Type Used        | PETROL                |
| Engine                | GO170F                |
| Engine Cylinder/Model | 1 cylinders - in line |
| Alternator Brand      | BUSINESS              |
| Phase                 | 220 MONOPHASE         |

### Engine Specifications

|                                      |            |
|--------------------------------------|------------|
| Oil Capacity (Including Filter) (lt) | 0.6 L      |
| Fuel Tank Capacity                   | 15 L       |
| Speed (r/min)                        | 3000/6000  |
| Cooling Method                       | AIR COOLED |
| Battery and Capacity (Quantity/V)    | 1x12       |
| System                               | String     |
| Battery Charging                     | 12 V       |

### Size And Weight

|             |     |
|-------------|-----|
| Width (mm)  | 605 |
| Length (mm) | 470 |
| Height (mm) | 435 |
| Weight (kg) | 46  |