



### About Product

In gasoline and diesel portable generators, the GO-BUSINESS GO-MOTOR generator set offers high performance and reliability. For all manufactured generator sets, prior product testing and factory manufacturing testing are carried out.

### POWER

| VOLTAGE | Standby Power (ESP) |      | Prime Power (PRP) |      | Amper | PWR (HP) |
|---------|---------------------|------|-------------------|------|-------|----------|
|         | kVA                 | kW   | kVA               | kW   | A     | hp       |
| 220     | 17,5                | 14,0 | 15,0              | 12,0 | 70,83 | 25,0     |

### General Features

|                       |                       |
|-----------------------|-----------------------|
| Model Name            | GO-DJ17000-2C         |
| Fuel Type Used        | DIESEL                |
| Engine                | GO2V92                |
| Engine Cylinder/Model | 1 cylinders - in line |
| Alternator Brand      | BUSINESS              |
| Phase                 | 220 MONOPHASE         |

### Engine Specifications

|                                      |            |
|--------------------------------------|------------|
| Oil Capacity (Including Filter) (lt) | 3,80 L     |
| Fuel Tank Capacity                   | 25,0 L     |
| MAX. OUTPUT (HP)                     | 25/3600rpm |
| Cooling Method                       | AIR COOLED |
| DC OUTPUT                            | 12V / 8.3A |
| Battery and Capacity (Quantity/V)    | 1x12       |
| Starting System                      | ELECTRIC   |

### Size And Weight

|             |     |
|-------------|-----|
| Width (mm)  | 925 |
| Length (mm) | 590 |
| Height (mm) | 810 |
| Weight (kg) | 196 |